

# LineSelect™ Model 9715 8-Channel RJ45 Cat5e Compliant A/B Switch, Manual, Individual Channel Control, Rackmount

- **Certified for Cat5e Compliance.**

## INTRODUCTION

The **LineSelect™** Model 9715 enables access to two 10/100/1000 Base-T networks. Each of the eight channels of the **LineSelect™** Model 9715 Cat5e A/B Switch allows the user to reroute data between two networks with a simple flip of a switch. The unit supports all 8 pins of the RJ45 Cat5e interface. No need to plug and unplug cables thereby eliminating connector wear. The Model **LineSelect™** 9715 is enclosed in a 1U, full rack size, all metal black chassis designed to provide EMI/RFI shielding and fit in a standard 19" rack.

## FEATURES:

- **Efficient use of panel space; eight complete A/B switches in 1U panel height (1.75").**
- Each channel allows quick connection to any one of two devices from one COMMON device.
- Rated for 10/100/1000 Base-T networks (Up to Cat 5e).
- **Certified for Cat 5e compliance.**
- All 8 pins of the RJ45 interface are switched via break-before-make rotary switch.
- The switch ports are transparent to all data.
- Individual Channel Control via eight knobs located on the front panel, one knob per channel.
- High quality sealed switch with self-wiping precious metal contacts.
- Manually operated. No power required.
- Attractive all metal black box packaging provides EMI/RFI shielding.
- **Lifetime warranty against manufacturing defects.**
- Custom length Cat5e cables available for your switch installation for improved system performance.



## SPECIFICATIONS:

**PORT CONNECTORS:** (24) RJ45 (F) connectors on rear panel; (8) COMMON ports, (8) "A" ports, (8) "B" ports.

**FRONT PANEL CONTROL:** (8) Rotary switches on front panel selects A or B for each channel.

**PINS SWITCHED:** All 8 pins switched.

**POWER:** No power required. Manually operated.

**DIMENSIONS:** Rackmount 19.0" W x 1.75" H x 8.59" D. (48.3 x 4.5 x 21.9 cm)

**WEIGHT:** Approximately 5.8 lbs (2.6 kg)

## LineSelect™ Model 9715 RJ45 Cat5e A/B Switch Application

